# JUNCTION BOXES

# Dynapak





Even greater flexibility and ease of installation with the new Dynapak, for posts with a min. inner diameter of 84mm\*.

The Dynapak can connect up to 2 x 25mm<sup>2</sup> network cables or 3 x 16mm<sup>2</sup> network cables and 2 lighting fixture cable outputs.

Integration of devices such as ADD protection, ST2, remote management, etc.

Open sides and stiffened back to facilitate connection.

Bottom cover easily fitted for secur maintenance of the connections.

with lamp output via the bottom (DPB) or the top (DPH).

Available in 2 versions:

Protective flexible cone to allow power cables to be inserted through the front.

#### **ADVANTAGES**

Terminal block support can be removed and height adjusted (two position levels), for easy connection and quick maintenance on site.

Transparent top cover to view and access protective devices. Central locking by ¼ turn captive screw.

Fixing bracket, tool-free adjustment over 110mm, with front or rear hooking.

#### TECHNICAL CHARACTERISTICS

#### Max. capacity

- · Up to 2 network cables, 4 x 25mm<sup>2</sup>.
- · Up to 3 x 5G16mm<sup>2</sup> network cables.
- $\cdot$  Up to 2 x 3G2.5mm<sup>2</sup> lighting fixture cables.

#### Casino

- · Polycarbonate, self-extinguishing.
- IP44 in accordance with IEC 60529 (open junction box: IP2X).
- IK08 in accordance with FN 62262.
- · Class 2.
- · -40°C to +130°C.

#### **Product standards**

· EN 61439-2.

#### Installation standards

· NF C17-200 and associated guides.

\* For vertical rail (rail-C): Min. int. Ø 89mm.

Standard colour

· Please contact us for other colours.

#### Mounting


- · Fixing bracket 1 or 2 hooks.
- Possible vertical rail mounting with M6 screws.

#### Optional

• Terminal block: marking of the terminals to facilitate maintenance.

#### Delivery

- Pre-wired with high-temperature silicone-coated wires and crimped lugs.
- · Supplied with cartridge fuses, configuration labels and cable clamp.





# LIGHTING FIXTURE OUTPUT **CABLES**

Via the bottom (DPB) or top (DPH).







Output at the top of the junction box

Main configura	ations
----------------	--------

	Standard	Options		
	Staridard	TET	Cable glands	
Via the BOTTOM (DPB)	2 cables (7 to 14mm)	-	-	
Via the TOP (DPH)	1 cable	2 cables (7 to 10mm - 2 x TET 7/10)	2 cables (6 to 12mm - 2 x M20)	
	(7 to 10mm - TET 7/10)	2 cables (10 to 14mm - 2 x TET 10/14)	1 cable (9 to 17mm - 1 x M25)	

# **CONNECTION** - Integrated terminals and terminal blocks



BE2 terminal block 2 to 4 x 2 inputs, 10mm<sup>2</sup> 2 to 4 x 3 inputs, 10mm<sup>2</sup> W 37mm



BE3 terminal block W 39mm



BD2 terminal block 2 to 4 x 2 inputs, 16mm<sup>2</sup> W 43mm



BD3 terminal block 2 to 4 x 3 inputs, 16mm<sup>2</sup> W 43mm



2 x 16 mm<sup>2</sup> inputs W 10.1mm



3 x 16mm<sup>2</sup> inputs W 10.1mm



4 x 16mm<sup>2</sup> inputs W 18.1mm



2 x 25mm<sup>2</sup> inputs W 11.7mm

## Main max. configurations

	≤ 16mm²	≤ 25mm²
2 network cables	4BD2 terminal block max. or 5 BD2 terminals max.	4 BC2 terminals max.
3 network cables	4BD3 terminal block max. or 5 BD3 terminals max.	-

Usable width of the connection zone: 54mm.

# PROTECTIONS & DEVICES - Max. volume available (mm): W 54 x D 48 x H 86



Surge Prote sogexi











W 18mm

W 18mm

W 36mm W 18mm

IDIL-10 W 28mm


W 28mm

#### Max. recommended combinations

		Ø	PFM W 18mm	IDIL W 28mm	ST2 W 28mm
FP or FN	W 18mm	1FP + 1FN	(FP + FN) + 1PFM**	-	-
FPN	W 18mm	3FPN**	2FPN + 1PFM**	1FPN + 1IDIL	1FPN + 1ST2
F2P	W 36mm	1F2P	1F2P + 1PFM**	-	-

Usable width of the protection zone: 54mm.

### **NETWORK CABLES**





#### Main max. configurations

	4X 10mm²	5G 10mm²	4X 16mm²	5G 16mm²	4X 25mm²	5G 25mm²	Lighting fixture cables
2 cables	•	•	•	•	•*	-	1
2 cables	•	•	•	•	•*	-	2
3 cables	•	•	•	● tok	-	-	1
3 cables	•	•	•	<b>●</b> **	-	-	2

<sup>\*</sup>With max. 3G 1.5mm<sup>2</sup> rigid lighting fixture cable.

<sup>\*\*</sup> Limit configurations: tight wiring.